


# Voltage Control Phase Shifter 0.5-1GHz

## Features

- Wide Band Operation 0.5-1GHz
- 180° Phase Shift
- Low Insertion Loss and Low Phase Error
- Single Control Operation
- Customization available upon request



Parameters	Min	Typ.	Max	Units
Frequency Range	0.5		1.0	GHz
Phase Range		180		deg
Phase Error		±20		deg
Insertion Loss		2.2	3.0	dB
Insertion Loss Temperature Coefficient		0.003		dB/ °C
Input VSWR		1.6	2.0	:1
Output VSWR		1.6	2.0	:1
0.1dB Compression Point (P0.1dB)			23	dBm
Control Voltage	DC-15			V
current	20			mA
Impedance	50			Ω
Weight	1.41			ounces
Input / Output Connectors	SMA-Female			
Finish	Gold plating			
Material	Aluminum			
Sealing	Hermetically Sealed (Optional)			

### Absolute Maximum Ratings

Control Voltage	0~ 18V
RF Input Power	30dBm

### Environmental Specifications


Operational Temperature	-40°C~+85°C
Storage Temperature	-50°C~+105°C
Altitude	30,000 ft. (Epoxy Sealed Controlled environment)
	60,000 ft. 1.0psi min (Hermetically Sealed Uncontrolled environment) (Optional)
Vibration	25g RMS (15 degrees 2KHz) endurance, 1 hour per axis
Humidity	100% RH at 35°C, 95%RH at 40°C
Shock	20G for 11msec half sine wave, 3 axis both directions

### Ordering Information


Part No.	Description
DBVCPS00500100A	0.5-1GHz Voltage Phase Shifter

### Outline Drawing:


All Dimensions in mm (inches)




### Insertion Loss @ +25°C




### Input VSWR @ +25°C




### Output VSWR @ +25°C




### Insertion Loss @ -40°C




### Input VSWR @ -40°C




### Output VSWR @ -40°C




### Insertion Loss @ +85°C




### Input VSWR @ +85°C




### Output VSWR @ +85°C




### Insertion Loss vs. Frequency




### Input VSWR vs. Voltage




### Output VSWR vs. Voltage



### Phase Shift vs. Frequency



### Phase Shift vs. Voltage



### Normalized Attenuation vs. Frequency

